

digitech

Rechargeable  
**Bluetooth® 5.0**  
**Headset**

with Charging Cradle



Model:  
**AA2180**

**Instruction Manual**

# Table of Contents

<b>Product Specification</b>	<b>1</b>
<b>Product Overview</b>	<b>2</b>
<b>Basic Operation</b>	<b>3</b>
<b>Bluetooth® Pairing and Connection</b>	<b>4</b>
<b>Connection with Two Devices</b>	<b>4</b>
<b>LED Indicator</b>	<b>5</b>
<b>Charging</b>	<b>5</b>
<b>On Call Functions</b>	<b>6</b>
<b>Q &amp; A</b>	<b>6</b>

## PRODUCT SPECIFICATION:

Bluetooth® Version:	V5.0
Operation Range:	10 meters
Battery Capacity:	180mAh/3.7V
Charging Time:	About 2 hours
Stand-by Time:	200 hours
Working Time:	About 15 hours at 50% volume*
Headset Weight:	About 47.5g
Headset Dimension:	158(H) x 148(W) x 51(D)mm
Charging Cradle Dimension:	83.5(H) x 83.5(W) x 30(D)mm

\*Actual use time will vary depending on volume level.

## PRODUCT OVERVIEW:



<b>1</b>	Microphone
<b>2</b>	Volume Down (-)
<b>3</b>	Volume Up (-)
<b>4</b>	LED Indicator

<b>5</b>	Micro USB Charge Port
<b>6</b>	Multi-function Button (MFB)
<b>7</b>	Charge Cradle Connector

## BOX CONTENTS:

1 x Bluetooth® 5.0 Headset

1 x Micro USB Charging Cable

1 x Charging Cradle

1 x User Manual

## BASIC OPERATION:

Button:	Function:	Operation Instruction:
Multi-Function Button (MFB)	Power On	When powered off, Long press for 1-4 seconds to power on (it will automatically try to reconnect to the last connected device when powered on)
	Power Off	When powered on, long press for 5 seconds to power off
	Enter into Pairing Mode	When powered off, long press 5-8 seconds to enter into pairing mode. Otherwise when in standby mode - unconnected, double press the MFB to enter pairing mode
	Play / Pause	Short press (when playing music)
	Redial a call	Double press to redial last number
	Reconnect	Power on and headset will reconnect to last connected device. Or short press MFB to reconnect in pairing mode.
	Voice Dialing	Long press for 1 second
	Audio Switch	Long press for 1 second to switch between phone and headset when during a calling
	Answer a call	Short press (when call coming)
	Hang up a call	Short press (during a call)
Volume Up (+)	Reject a call	Long press 1 second (when call coming)
	Volume Up	Short press
Volume Down (-)	Next Song	Long press for 1 second
	Volume Down	Short press
Volume Down (-)	Previous Song	Long press for 1 second
	Microphone Mute	In calling, short press "Volume +" and "Volume -" to mute the mic, operate again to cancel the mute.

## BLUETOOTH® PAIRING AND CONNECTION:

1. When powered off, long press Multi-Function Button for 5-8 seconds to enter pairing mode with LED Blue & Red flash alternately.
2. Search and connect to “AA2180” in your device Bluetooth® settings, LED change to LED Blue flash once connected, now you can now take calls or play music through the headphone.
3. You can press MFB / volume (+) / volume (-) on the Bluetooth® headset to control the answer/hang up a call and play/pause of the music, next and previous song, volume up and down.

### **Note:**

Pairing: In off status, long press MFB for 5-8 seconds to enter into pairing mode with LED Blue & Red alternately flash.

Connection: Search and click to connect “AA2180” on your device’s Bluetooth® list.

## CONNECTION WITH TWO DEVICES:

1. Using the instructions above connect the first device via Bluetooth®, and turn off the Bluetooth® function of the first device.
2. Set the Bluetooth® Headset to pairing mode again, in standby mode - unconnected, double press MFB to enter pairing mode with Red & Blue LED flash alternately.
3. Search and click to connect “AA2180” on your second device Bluetooth® lists, LED change to Blue LED slow flash after connected.
4. Turn on Bluetooth® function of first device, click to reconnect “AA2180” on Bluetooth® lists. Headset is connected with two devices now.

**Note:** \*Music only can be played from one device under two connections, when you want to play music from another device, you need to pause or close the music of the previous device. The same operation during talking status.

## BASIC OPERATION:

Mode:	LED Indicator:
Power on	LED Blue flash 1 second
Power off	LED Red flash 1 second
Pairing mode	LED Red & Blue flash alternately
Unconnected standby mode	LED Blue flash once every 2 seconds
Connected standby mode	LED Blue flash once every 5 seconds
Playing Music	LED Blue flash once every 5 seconds
Talking	LED Blue flash once every 5 seconds
Delete paired record	Blue and Red LED flash once at the same time
Charging	Solid LED Red
Full charged	Solid LED Blue
Low battery	Red LED flash

## CHARGING:

Charge the Bluetooth® Headset once when the Red LED flash. Charging time about 2 hours. Solid Red LED changes to Solid Blue LED when fully charged.

### Charge Connections:

Please connect to the Bluetooth® Headset charging port through the Micro USB charging cable, the charger can be used as car charger, travel charger, computer USB, etc.

### Use of Charging Cradle:

Place the Bluetooth® Headset on the charging base, then connect the charging base to USB charger through the Micro USB port for charging.

### Note:

1. Please charge the Bluetooth® Headset at least one time every 3 months when not in use.
2. Charging when Headset it is powered on, will reset it automatically and power off.

## ON CALL FUNCTIONS:

### Calling function operation

- Short press the MFB to answer the new call and hang up the current call;
- Double press the MFB to answer the new call and keep the current call;
- Long press the MFB for 1 second to reject a new call while in current call.
- When you are on a three-party call, double press the MFB to switch audio between the current call and the keep call.

## Q & A:

### 1. How to reconnect and operation when failed to reconnect ?

When Bluetooth® Headset is connected with your device successfully for the first time, it will search and reconnect the paired device automatically when power on, If failed, please pair and connect again.

### 2. How to delete paired records?

When powered on, long press the volume + and the volume - button for 5 seconds to clear the pairing record. The indicator Blue and Red LED flash once at the same time that means the pairing record has been cleared, and the Bluetooth® Headset will not connect back to the connected device. When there are various connection problems, try clearing the pairing record.

### 3. What's the password for pairing?

Some connection devices require password for pairing, please try the following: 0000 or 8888 or 1111 or 1234.

### 4. What devices could charge for the headphone?

Any car charger, power bank, PC etc which meet DC 5V, charging current more than 500mA could be charge for this item.

### 5. How to reset the headset?

Press MFB and plug the charge cable when powered on, it will reset the headset and power off.

Distributed by:  
Electus Distribution Pty. Ltd.  
320 Victoria Rd, Rydalmere  
NSW 2116 Australia

[www.electusdistribution.com.au](http://www.electusdistribution.com.au)

Made in China